

Sigen Hybrid Inverter

50.0 / 60.0 / 80.0 / 100.0 / 110.0 kW



- Seamless switchover, ensuring 0ms load-side disruption operation
- 150% overload for 10s, handling impact loads for smooth device startup
- Minimal size & weight in the same power range, ensures simple installation
- Multi-unit connection via Energy Gateway, flexible expansion from kW to MW
- DC coupling micro-grid solution, simplifies configuration & boosts efficiency

Signen Hybrid Inverter 50.0 / 60.0 / 80.0 / 100.0 / 110.0 kW

Preliminary

| Signen PV | 50M1-HYB | 60M1-HYB | 80M1-HYB | 100M1-HYB | 110M1-HYB | Units |
|---|---|----------|----------|-----------|-----------|-------------|
| DC Input (PV) | | | | | | |
| Max. PV input power | 100,000 | 120,000 | 160,000 | 200,000 | 220,000 | Wp |
| Max. DC input voltage | | | | 1,100 | | |
| Nominal DC input voltage | 600 @380/400 Vac, 720 @480 Vac | | | | | V |
| Start-up voltage | | | | | | 180 |
| MPPT voltage range | | | | | | 160 ~ 1,000 |
| Number of MPP trackers | 4 | 5 | 6 | 8 | 8 | |
| Number of PV strings per MPPT | | | | | | 2 |
| Max. input current per MPPT | | | | | | 40 |
| Max. short-circuit current per MPPT | | | | | | 60 |
| DC Input (Battery) | | | | | | |
| Battery module models | SignenStack BAT 12.0 | | | | | |
| Battery controller models | SignenStack BC M2-0.5C-BST / SignenStack BC M2-1C-BST | | | | | |
| System configuration quantity range | | | | | | 4 ~ 21 |
| Max. charge power | 55,000 | 66,000 | 88,000 | 110,000 | 121,000 | W |
| Max. discharge power | 55,000 | 66,000 | 88,000 | 110,000 | 121,000 | W |
| Max. operating current | | | | | | 180 |
| AC Output (On-grid) | | | | | | |
| Nominal output active power | 50,000 | 60,000 | 80,000 | 100,000 | 110,000 | W |
| Max. output apparent power | 55,000 | 66,000 | 88,000 | 110,000 | 121,000 | VA |
| Max. output active power (cosΦ=1) | 55,000 | 66,000 | 88,000 | 110,000 | 121,000 | W |
| Nominal output current @380Vac | 76.0 | 91.2 | 121.5 | 151.9 | 167.1 | A |
| Nominal output current @400Vac | 72.5 | 87.0 | 115.9 | 144.9 | 159.4 | A |
| Nominal output current @480Vac | 60.2 | 72.2 | 96.3 | 120.3 | 132.4 | A |
| Max. output current @380 / 400Vac | 83.6 | 100.3 | 133.7 | 167.1 | 183.8 | A |
| Max. output current @480Vac | 66.2 | 79.4 | 105.9 | 132.4 | 145.6 | A |
| Nominal output voltage | 380 / 400 / 480, 3W+N+PE | | | | | Vac |
| Nominal grid frequency | 50 / 60 | | | | | Hz |
| Power factor | 0.8 leading ~ 0.8 lagging | | | | | |
| Total current harmonic distortion | THDi < 3% | | | | | |
| AC Output (Backup) | | | | | | |
| Nominal output active power | 50,000 | 60,000 | 80,000 | 100,000 | 110,000 | W |
| Max. output apparent power | 55,000 | 66,000 | 88,000 | 110,000 | 121,000 | VA |
| Peak output power (10 seconds) | 75,000 | 90,000 | 120,000 | 150,000 | 150,000 | W |
| Nominal output voltage | 380 / 400 / 480, 3W+N+PE | | | | | V |
| Nominal output frequency | 50 / 60 | | | | | Hz |
| Power factor | 0.8 leading ~ 0.8 lagging | | | | | |
| Total voltage harmonic distortion | THDv < 3% | | | | | |
| Disruption time of backup switch ² | 0 | | | | | ms |
| Efficiency | | | | | | |
| Max. efficiency | | | | | | 98.3% |
| European efficiency | 97.9% | 97.9% | 98.0% | 98.0% | 98.0% | |
| Protection | | | | | | |
| Safety protection feature | DC reverse polarity protection, Insulation monitoring, Residual current monitoring, Arc fault circuit interrupter, AC overcurrent/overvoltage/short-circuit protection. Type II DC/AC surge protection, Anti-islanding protection | | | | | |
| General Data | | | | | | |
| Dimensions (W / H / D) | 1110 / 668 / 348 | | | | | mm |
| Weight | 105 | | | | | kg |
| Storage temperature range | -40 ~ 70 | | | | | °C |
| Operating temperature range | -30 ~ 60 | | | | | °C |
| Relative humidity range | 0% ~ 100% | | | | | |
| Max. operating altitude | 5,000 (Derating at 4,000m) | | | | | m |
| Cooling | Smart air cooling | | | | | |
| Ingress protection rating | IP66 | | | | | |
| Communication | WLAN / Fast Ethernet / RS485 / Signen CommMod (4G/3G/2G) | | | | | |

1. This refers to the load-side disruption time. Test conditions: In the open-circuit state of the power grid, the nominal power of the Signen Hybrid Inverter is higher than the total power of the loads.
2. For Signen energy gateway connections, the inverter should be connected to the gateway via its AC output port (Grid).
3. The information in this document reflects the current state of technology and is subject to change without notice. For the latest updates, please refer to the Signenergy website.

Disclaimer: The information in this file is provided on an "as is" basis. To the fullest extent permitted by law, Signenergy Technology Co., Ltd. excludes all representations and warranties relating to this file and its contents or which is or may be provided by any affiliates or any other third party, including in relation to any inaccuracies or omissions in this file.